



**WACKER
NEUSON**
all it takes!



Electric motor M2500

5100010890

[Home](#) >> [Catalog](#) >> [Products](#) >> [Concrete Technology](#) >> [Internal Vibrators](#) >> [Modular Internal Vibrators](#) >> **Electric motor M2500**

Electric motor M2500

Material number 5100010890



Powerful electric motor for the modular internal vibrator HMS.

Product details

- Housing made of high-strength, break-proof synthetic material, compactly and ergonomically shaped
- Protected against splash water from all directions (IP 24)
- Extremely long service life of the carbon brushes (up to 500 operating hours)
- Air cleaner replacement from the outside
- Rapid action coupling for tool-free connection of the flexible shaft

You will find a large selection of matching flexible shafts and vibrator heads here in the shop.

Please note: the modular internal vibrator HMS consists of three components: motor, flexible shaft and vibrator head.

You will find possible combinations of motors (M), vibrator heads (H) and flexible shafts (SM) in the table above (see picture).

Comes with

- motor
- Operator's manual

(Flexible shaft and vibrator head not included in the standard package)

Technical specifications

Electric motor M2500

ELECTRICAL SYSTEM

Light cone	0,5 m
Length Cable	0,50 m
Kind of plug	CEE-Plug 2P+E 16A 110V 4H

MECHANICAL DETAILS

Length	312 mm
Width	154 mm
Height	230 mm
Weight	5,40 kg

ELECTRICAL - OUTPUT DETAILS

Nominal current	15,00 A
Nominal voltage	120 V
Nominal frequency	50 - 60 Hz
Phase	1 ~

MOTOR

Motor type	universal motor
Nominal power	1,800 KW
Nominal speed	12.000 1/min
Idle speed	16.000 1/min

ENVIRONMENT DATA

Protection class	II / Protective insulation
Degree of protection	IP24
Sound level LpA	85,0 dB(A)
Sound level LpA (Standard)	DIN EN ISO 11201
Vibration total value ahv	5,0 m/s ²
Vibration value ahv (Standard)	DIN EN ISO 20643
Uncertainty in measurement HAV	1,0 m/s ²

Please Note

This product availability can vary from country to country. It is possible that information / products may not be available in your country. More detailed information on engine power can be found in the operator's manual; the started power may vary due to specific operating conditions Subject to alterations and errors expected. Applicable also to illustrations.

Copyright © 2018 Wacker Neuson SE